



A Benny Lee Company

PRODUCT USER GUIDE

RMF-4012

AC to DC Power Supply

Owners Guide

(These instructions are intended for use by a technician familiar with electronic products)

- Auto range voltage input 85 to 264 VAC, 47 to 63 Hz or 120 to 370 VDC
- Available in 12, 24, 48 VDC output (adjustable)
- Built-in TTL remote control / remote sense
- DC-OK TTL signal
- Short circuit / over load / over voltage / over temperature protections
- 3 year warranty



DESCRIPTION

The RMF-4012 has an auto range voltage input of 85 to 264 VAC, with 47 to 63 Hz or 120 to 370 VDC. This unit comes with three available outputs that are adjustable; these outputs are available in 12, 24, and 48 VDC. All RMF devices have a built-in TTL remote control and remote sense along with a DC-OK TTL signal, along with short circuit, over load, over voltage, over temperature protections, and hold UL, CE, TUV, CUL approvals. To guarantee DuraComm's durability DuraComm offers a 3 year warranty for all of their RMF series products.

SPECIFICATIONS

Output Voltage	13.8 VDC
Output Adjustment Range	11 to 14.5 VDC
Output Voltage Tolerance	+/- 1 pct
Output amperage, max continuous	45 Amps
Maximum Power, continuous	600 Watts
Maximum ripple and noise	120 mV p-p max
Input voltage range (auto-ranging)	85-264 VAC
Input frequency range	47-63 Hz
Maximum AC current.....	8.5 Amps/115 VAC; 5 Amps/230 VAC
Typical Efficiency	88 %
Max inrush current, single cycle	35 Amps @ 115 VAC, 70 Amps @ 230 VAC
Overload Protection (operates)	typical 85 to 115 %, Constant Current Limiting, Recovers Automatically
Line Regulation	0.3 %
Load Regulation	0.5 %
Fan Control	LOAD 35+/-15% or RTH2>/=50 C, Fan On
Over Temperature	+80 C Power Transistor or +100 C Output Choke, Shutdown Output Voltage, Automatic Recovery
Rise Time following ON (Full Load)	50 mS
Hold Time following OFF (Full Load)	16mS
Working Temperature range	-40 to 158 F (-40 C to +70 C)
Storage Temperature	-40 C to 185 F (-40 to +85 C)
Withstand Voltage	3 KVAC @ 10 ma (I/P-O/P)
(Continued)	2 KVAC @ 10 ma (I/P-F/G)
(Continued)	500 VAC @ 10 ma (O/P-FG)
Dimensions	3.5H x 19W x 5.25D inches, nominal
Weight	7 lbs, nominal

INSTALLATION WARNING

The individual user should take care to determine, prior to use or installation, whether this device is suitable, adequate or safe for the use intended. Since individual applications are subject to great variation, DuraComm makes no representation or warranty as to the merchantability, suitability or fitness of these units for any specific application.

The precision regulated power supplies operate internally from voltages in excess of 300 volts. In rare cases, voltage spikes or transients on the AC power line, or overheating, may cause a component failure in the power supply. Overloading the output will cause the over current feature to operate. In either case, the cause must be determined and corrected. Failures require investigation as to cause and/or repair of the unit.

THERE ARE NO USER SERVICEABLE PARTS INSIDE. HAZARDOUS VOLTAGES EXIST INSIDE THE UNIT. SERVICE AND REPAIR MUST BE REFERRED TO QUALIFIED FACTORY PERSONNEL.

INSTALLER NOTES

The outputs are **NOT** referenced to the chassis. The Modular System can be used either positive or negative ground.

DO NOT block any of the cooling vents on the sides and always allow adequate ventilation by not installing the unit inside tightly closed spaces. Physical mounting position is not critical but the cooling vents and the load controlled cooling fan must not be blocked.

AC MAIN OPERATING INPUT VOLTAGE

The AC input is auto-ranging and will operate without adjustment from 85 VAC to 264 VAC. Maximum efficiency is realized with input voltages above 180 VAC. Linear de-rating to ~85% @ 90 VAC is recommended for AC inputs less than 180 VAC.

CONDUCTOR ATTACHMENT

The DC output terminals are 6mm diameter and a ¼ inch ring terminal will fit exactly. The ¼ inch ring terminal may be crimped or soldered to the conductors before attaching to the DC output terminals. **DO NOT** solder the ring terminals while on the DC output studs. Use a 10 mm wrench to securely tighten the hex nut on the stud.

RECOMMENDED COPPER WIRE SIZE FOR CURRENT CAPACITY

(Insulated Wire, Single Conductor in free air)

<u>Current Level in Amperes</u>	<u>Wire Size</u>
<7 AMPERES	20 AWG Up to 5 feet 18 AWG Up to 10 feet
14 AMPERES	18 AWG Up to 5 feet 16 AWG Up to 10 feet
20 AMPERES	16 AWG Up to 5 feet 14 AWG Up to 10 feet
30 AMPERES	14 AWG Up to 5 feet 12 AWG Up to 10 feet
40 AMPERES	12 AWG Up to 5 feet 10 AWG Up to 10 feet
50 AMPERES	10 AWG Up to 5 feet 8 AWG Up to 10 feet
70 AMPERES	8 AWG Up to 5 feet 6 AWG Up to 10 feet
100 AMPERES	6 AWG Up to 5 feet 4 AWG Up to 10 feet

LIMITED WARRANTY

DuraComm warrants to the initial end user, each power supply manufactured by DuraComm to be free from defects in material and workmanship, when in normal use and service for a period of three years from the date of purchase, from an authorized DuraComm dealer.

Should a product manufactured by DuraComm fail or malfunction due to manufacturing defect, or faulty component, DuraComm, at its option, will repair or replace the faulty product or parts thereof, which, after examination by DuraComm, prove to be defective or not operational according to specifications in effect at the time of sale to the initial end user. The product that is replaced or repaired under the provisions of this warranty, will be warranted for the remainder of the original warranty period, only, and will not extend into a new three year warranty period.

The limited warranty does not extend to any DuraComm product which has been subject to misuse, accidental damage, neglect, incorrect wiring not associated with manufacture, improper charging voltages, or any product which has had the serial number removed, altered, defaced, or changed in any way.

DuraComm reserves the right to change, alter, or improve the specifications of its products at any time, and by so doing, incurs no obligation to install or retrofit any such changes or improvements in or on products manufactured prior to inclusion of such changes.

DuraComm requires any product needing in or out of warranty service to be returned to DuraComm. All requests for warranty service must be accompanied by proof of purchase, such as bill of sale with purchase date identified. DuraComm is not responsible for any expenses or payments incurred for the removal of the product from its place of use, transportation or shipping expenses to the place of repair, or return expenses of a repaired or replacement product to its place of use.

The implied warranties which the law imposes on the sale of this product are expressly LIMITED, in duration, to the three (3) year time period specified herein. DuraComm will not be liable for damages, consequential or otherwise, resulting from the use and operation of this product, or from the breach of this LIMITED WARRANTY.

Some states do not allow limitations on the duration of the implied warranty or exclusions or limitations of incidental or consequential damages, so said limitations or exclusions may not apply to you. This warranty gives you specific legal rights which vary from state to state.

This warranty is given in lieu of all other warranties, whether expressed, implied, or by law. All other warranties, including WITHOUT LIMITATION, warranties of merchantability and fitness or suitability for a particular purpose, are specifically excluded. DuraComm reserves the right to change or modify its warranty and service programs without prior notice.

DuraComm® Corporation

6655 Troost Avenue

Kansas City, MO 64131

Phone (816) 472-5544 Fax (816) 472-0959

www.duracomm.com