



A Benny Lee Company

PRODUCT USER GUIDE

DCDC-48-48 DCDC Converter Owners Guide

(These instructions are intended for use by a technician familiar with electronic products)

- 1000 Watts of power
- Protection: short circuit/overload/over temperature
- Output DC OK signal (open collector signal)
- Remote Control On/Off
- Thermostat control forced air cooling
- Low Voltage Disconnect
- Meter: Voltage/Amperage selectable
- 2000 VAC I/O isolation
- 3 year warranty



DESCRIPTION


The DCDC-48-48 is a 2U rack mount DC-to-DC converter power supply that is capable of 1000 watts of power. It has isolated inputs and outputs, so it can be used in positive ground installations. The LVD is pre-set to disconnect the load at 42.0 VDC. However, to prevent premature or false disconnect when the input source voltage drops below the 42.0 volt threshold a two-minute timer is started. If the input source recovers to above 42.0 volts, the timer resets and waits. The timed delay ensures the input source voltage is not disconnected until necessary to prevent damage. After the main input source voltage is restored, the LVD will reconnect the load when the input source voltage exceeds 50.0 volts.

SPECIFICATIONS

Input Voltage Range.....	40-60 VDC
Input Current	23.0 Amps
Output Voltage to Load.....	48.0 VDC
Output Current.....	20.0 Amps Max
Line Regulation	+/- 0.5%
Max inrush current, single cycle	100 Amps
Efficiency	90 %
Low Voltage Disconnect.....	42.0 VDC
Low Voltage Reconnect.....	50.0 VDC
Working Temperature range.....	-4 F to +140 F (-20 C to +60 C)
Storage Temperature	-40 F to +185 F (-40 C to +85 C)
Size	11" D x 19" W x 3.5" H
Weight	12.0 Lbs

DC-OK AND REMOTE CONTROL

- Open collector signal (pin4), referenced to GND (pin3). Low when PSU turns on.
- The maximum sink current is 10mA and the maximum external voltage is 13V.



Output DC OK signal	DC-OK
G Reference point	G
Remote control ON/OFF SW Close Output "OFF" SW Open Output "ON"	RC1,RC2

INSTALLATION WARNING

The individual user should take care to determine, prior to use or installation, whether this device is suitable, adequate or safe for the use intended. Since individual applications are subject to great variation, DuraComm makes no representation or warranty as to the merchantability, suitability or fitness of these units for any specific application.

DO NOT block any of the cooling vents on the sides and always allow adequate ventilation by not installing the unit inside tightly closed spaces. Physical mounting position is not critical but the cooling vents must not be blocked. Make certain the input voltage is the correct voltage BEFORE applying DC power.

CONDUCTOR PRETREATMENT

All kinds of copper conductors can be clamped without treatment. DO NOT solder tin stranded conductors. The solder yields and fractures under high pressure. The result is increased contact resistance and excessive temperature rise. Additionally, corrosion has been observed due to the fluxes. Notch fractures at the transition from the rigid tinned part to the flexible conductors are also possible. Ferrules can be used as a protection when wiring stranded conductors. Copper ferrules prevent the current transfer from being influenced by dissimilar metals and remove the risk of corrosion. Always use the correct tool to crimp the ferrule.

RECOMMENDED COPPER WIRE SIZE FOR CURRENT CAPACITY

(Insulated Wire, Single Conductor in free air)

<u>Current Level in Amperes</u>	<u>Wire Size</u>
<7 AMPERES	20 AWG Up to 5 feet 18 AWG Up to 10 feet
14 AMPERES	18 AWG Up to 5 feet 16 AWG Up to 10 feet
20 AMPERES	16 AWG Up to 5 feet 14 AWG Up to 10 feet
30 AMPERES	14 AWG Up to 5 feet 12 AWG Up to 10 feet
40 AMPERES	12 AWG Up to 5 feet 10 AWG Up to 10 feet
50 AMPERES	10 AWG Up to 5 feet 8 AWG Up to 10 feet
70 AMPERES	8 AWG Up to 5 feet 6 AWG Up to 10 feet
100 AMPERES	6 AWG Up to 5 feet 4 AWG Up to 10 feet

LIMITED WARRANTY

DuraComm warrants to the initial end user, each power supply manufactured by DuraComm to be free from defects in material and workmanship, when in normal use and service for a period of three years from the date of purchase, from an authorized DuraComm dealer.

Should a product manufactured by DuraComm fail or malfunction due to manufacturing defect, or faulty component, DuraComm, at its option, will repair or replace the faulty product or parts thereof, which, after examination by DuraComm, prove to be defective or not operational according to specifications in effect at the time of sale to the initial end user. The product that is replaced or repaired under the provisions of this warranty, will be warranted for the remainder of the original warranty period, only, and will not extend into a new three year warranty period.

The limited warranty does not extend to any DuraComm product which has been subject to misuse, accidental damage, neglect, incorrect wiring not associated with manufacture, improper charging voltages, or any product which has had the serial number removed, altered, defaced, or changed in any way.

DuraComm reserves the right to change, alter, or improve the specifications of its products at any time, and by so doing, incurs no obligation to install or retrofit any such changes or improvements in or on products manufactured prior to inclusion of such changes.

DuraComm requires any product needing in or out of warranty service to be returned to DuraComm. All requests for warranty service must be accompanied by proof of purchase, such as bill of sale with purchase date identified. DuraComm is not responsible for any expenses or payments incurred for the removal of the product from its place of use, transportation or shipping expenses to the place of repair, or return expenses of a repaired or replacement product to its place of use.

The implied warranties which the law imposes on the sale of this product are expressly LIMITED, in duration, to the three (3) year time period specified herein. DuraComm will not be liable for damages, consequential or otherwise, resulting from the use and operation of this product, or from the breach of this LIMITED WARRANTY.

Some states do not allow limitations on the duration of the implied warranty or exclusions or limitations of incidental or consequential damages, so said limitations or exclusions may not apply to you. This warranty gives you specific legal rights which vary from state to state.

This warranty is given in lieu of all other warranties, whether expressed, implied, or by law. All other warranties, including WITHOUT LIMITATION, warranties of merchantability and fitness or suitability for a particular purpose, are specifically excluded. DuraComm reserves the right to change or modify its warranty and service programs without prior notice.

DuraComm® Corporation

6655 Troost Avenue
Kansas City, MO 64131
Phone (816) 472-5544 Fax (816) 472-0959
www.duracomm.com