



A Benny Lee Company

LP-18BC

SWITCHING DESKTOP WITH CHARGING/LOW VOLTAGE DISCONNECT



Weight - 3.5 lbs
1.97" H x 7.09" W x 8.54" D



BASIC FEATURES

- Filtered and Regulated
- Adjustable Output Voltage
- Overload / Over Temperature / Over Voltage / Short Circuit Protections
- Compatible with all DuraComm LPH Hoods for custom mounting of all mobile radios

BATTERY CHARGER FEATURES

- AC Input Voltage 115 or 230 VAC Switch selectable
- Battery Backup charging Circuit / LVD provide protective isolation and seamless transfer to battery when AC power is lost. Automatically provides float charge, battery maintenance when AC power is restored

BATTERY RECOMMENDATION

- 50 Amp/hr

SPECIFICATIONS

Model Number	Output Current (Amps)	Output Voltage VDC	Input Voltage VAC	Charging Output VDC	Charging Current Amps	Internal Battery	Weight (lbs)
LP-18BC	13.5 (15A- No Batt)	Ch1=13.8 Ch2=13.6	115 or 230	13.6	1.5	N/A	3.5